

DATUM DIAL BULLET/CARTRIDGE DIALS - FORSTER PRODUCTS, INC. #1 BULLET/CARTRIDGE DIAL

[Reloading](#) > [Measuring Tools](#) > [Bullet Comparators](#)

These separate Bullet/Cartridge dials are to be used with the Forster Datum Dial Ammunition Measurement System. These Bullet/Cartridge dials are used to measure the relative distance of a bullet or loaded cartridge from the base of the bullet/cartridge to the bullet's ogive. Dial #2 can be used with 17 Caliber, 20 Caliber, 25 Caliber, 270 Caliber, 6.8mm, and 338 Caliber Bullets.



Attributes

- Name: [FORSTER PRODUCTS, INC. #1 BULLET/CARTRIDGE DIAL](#)
- Manufacturer: [FORSTER PRODUCTS, INC.](#)
- Product no.: 749013804
- Mfr. No.: DD1111
- Delivery weight: 0.045kg
- Shipping height: 12mm
- Shipping width: 76mm
- Shipping length: 128mm
- UPC: 757253992520

Item details

Made in USA

Table of Contents

- Startpage
- Safety Instruction Guide for DATUM DIAL BULLET/CARTRIDGE DIALS
- About Us

Safety Instruction Guide for DATUM DIAL BULLET/CARTRIDGE DIALS

Introduction

Thank you for choosing the DATUM DIAL BULLET/CARTRIDGE DIALS from Forster Products, Inc. This guide provides essential safety instructions and usage information to ensure the safe and effective use of your Bullet/Cartridge Dials. It is crucial to follow these guidelines to prevent accidents and ensure proper functioning.

General Safety Guidelines

- **Product Safety:** Always ensure that the dials are used as intended and in accordance with the manufacturer's instructions.
- **Enhanced Recalls:** Stay informed about any product recalls or safety notices related to your dials. Check the EU Safety Gate platform for updates.
- **Online Shopping Protections:** If purchased online, ensure that the retailer complies with all safety requirements.
- **Special Consumer Focus:** These dials are not intended for use by children. Keep out of reach of minors.
- **EU Contact Point:** For safety inquiries, refer to the contact point provided by the retailer or manufacturer.
- **Rapid Alerts:** Be aware of the Safety Gate system for quick updates on unsafe products.

Specific Safety Precautions for Use

- **Hazard Identification:**
 - Risk of injury if the dials are used incorrectly.
 - Potential for damage to the dials if dropped or mishandled.
- **Avoiding Hazards:**
 - Always handle the dials with care.
 - Do not use the dials if they are damaged or show signs of wear.
 - Ensure that the dials are used in a clean, dry environment to prevent contamination.

Instructions for Installation and Usage

1. Installation:

- Ensure that the ammunition measurement system is set up according to the manufacturer's guidelines.
- Attach the Bullet/Cartridge dial securely to the measurement system.

2. Usage:

- To measure the distance from the base of the bullet/cartridge to the ogive, carefully insert the bullet or cartridge into the dial.
- Rotate the dial to obtain the measurement, ensuring that it is aligned properly for accurate results.
- Record the measurement as needed for your reloading or ammunition assessment.

3. Maintenance:

- Clean the dials regularly with a soft cloth to remove any debris.
- Store the dials in a protective case when not in use to prevent damage.

Disposal Instructions

- Dispose of the dials in accordance with local regulations.
- Do not dispose of in regular household waste if they are damaged or contain hazardous materials.
- Check with local authorities for proper disposal methods.

Contact Information for Further Support

For any questions or concerns regarding the use of the DATUM DIAL BULLET/CARTRIDGE DIALS, please refer to the contact information provided by your retailer or the manufacturer.

By following these safety guidelines and instructions, you can ensure the safe and effective use of your DATUM DIAL BULLET/CARTRIDGE DIALS. Thank you for your attention to safety!

About Us

Brownells UK

Brownells UK - World's Largest Supplier of Gun Parts, Gunsmith Tools & Shooting Accessories

Unit 1, Laughing Dog Industrial Estate
London Road
Rugby
Warwickshire
CV23 9LP

www.brownells.co.uk